



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets



IP & S-DE zugestellt	
am	23. Juni 2003
Frist	

Bescheinigung

Certificate

Attestation

Die angehefteten Unterla-
gen stimmen mit der
ursprünglich eingereichten
Fassung der auf dem näch-
sten Blatt bezeichneten
europäischen Patentanmel-
dung überein.

The attached documents
are exact copies of the
European patent application
described on the following
page, as originally filed.

Les documents fixés à
cette attestation sont
conformes à la version
initialement déposée de
la demande de brevet
européen spécifiée à la
page suivante.

Patentanmeldung Nr. Patent application No. Demande de brevet n°

02017272.2

PRIORITY DOCUMENT
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH
RULE 17.1(a) OR (b)

Der Präsident des Europäischen Patentamts;
Im Auftrag

For the President of the European Patent Office

Le Président de l'Office européen des brevets
p.o.

R C van Dijk



Europäisches
Patentamt

European
Patent Office

Office européen
des brevets

**Blatt 2 der Bescheinigung
Sheet 2 of the certificate
Page 2 de l'attestation**

IP & S-DE zugestellt	
am	23. Juni 2003
Frist	

Anmeldung Nr.:
Application no.:
Demande n°: **02017272.2**

Anmeldetag:
Date of filing:
Date de dépôt: **01/08/02**

Anmelder:
Applicant(s):
Demandeur(s):
Philips Intellectual Property & Standards GmbH
20099 Hamburg
GERMANY
Koninklijke Philips Electronics N.V.
5621 BA Eindhoven
NETHERLANDS
Bezeichnung der Erfindung:
Title of the invention:
Titre de l'invention:

In Anspruch genommene Priorität(en) / Priority(ies) claimed / Priorité(s) revendiquée(s)

Staat:
State:
Pays:

Tag:
Date:
Date:

Aktenzeichen:
File no.
Numéro de dépôt:

Internationale Patentklassifikation:
International Patent classification:
Classification internationale des brevets:

/

Am Anmeldetag benannte Vertragsstaaten:
Contracting states designated at date of filing:
Etats contractants désignés lors du dépôt:

AT/BG/BE/CH/CY/CZ/DE/DK/EE/ES/FI/FR/GB/GR/IE/IT/LI/LU/MC/NL/

Bemerkungen:
Remarks:
Remarques:

The applicant's name at the time of filing of the application was as follows: **Philips Corporate Intellectual Property GmbH.**

The registration of the changes has taken effect on **13.03.03.**

See for the original title of the application, page 1 of the description.

DESCRIPTION

IP & S - DE zugestellt	
am	23. Juni 2003
Frist	

EPO - Munich
80

01. Aug. 2002

Dual mode tuning arrangement.

The invention relates to a dual mode tuning arrangement for tuning to VHF television signals and to FM radio signals, said arrangement having a local oscillator circuit

5 comprising a first series arrangement of first and second inductances, a second series arrangement of a variable capacitance diode and a first padding capacitor, said first and second series arrangements being interconnected at first and second junctions to constitute a parallel arrangement, an active oscillator element being connected between the first junction of said parallel arrangement and ground, a third series arrangement of a

10 mode switching diode and a second padding capacitor connected in parallel with one of said first and second inductances, means for supplying a tuning voltage to the junction of the variable capacitance diode and the first padding capacitor and means for supplying a mode switching voltage to the junction of the mode switching diode and the second padding capacitor. Such dual mode tuning arrangement is used in applicant's publicly

15 available TV-FM tuner FM1200MK2.

In an arrangement of the abovementioned kind it is desirable to use the same local-oscillator circuit for both modes because the FM radio-band (88 - 110 MHz) lies between the VHF TV-bands. However, a different intermediate frequency is required for

20 the reception of TV signals and the reception of FM signals. For reception of FM signals the intermediate frequency is 10,7 MHz whereas for the reception of TV signals the intermediate frequency is either 38,9 MHz (European PAL-standard) or 45,75 MHz (US NTSC-standard). Therefore the local oscillator circuit needs to be switched so that the local oscillator frequency is lower in the FM mode than in the TV mode. This is the

25 function of the mode switch.

The nature of simple mode tuned circuits is that they have very high impedance at resonance while on either side of the resonance frequency the impedance quickly decays

to very low levels. Hence in those circuits only a single oscillation is sustained. However, in dual mode tuned circuits of the abovementioned kind, unwanted or parasitic oscillations may easily occur and these parasitic oscillations have to be sufficiently damped. This is particularly critical in applications where a phase locked loop (PLL) synthesizer measures the actual frequency and uses the result to line up the tuned circuit. If the PLL would acquire an undesired oscillation it can be driven into „lock up“.

In the abovementioned publicly known tuning arrangement a provision is made to damp parasitic oscillations by grounding the junction point between the two inductances through a relatively low-value damping resistor. However it appeared that this solution is not sufficiently satisfactory. The active oscillation element (the PLL) is usually realized in integrated form and it appears that with modern PLL synthesizer IC's with improved high frequency performance the known dual mode tuned circuit still has substantial problems with parasitic oscillations. Increasing the value of the damping resistor may increase the damping of parasitic oscillation, however this solution would result in more noise with lower performance of the oscillator. Another problem is that there is a practical upper limit to the value of the damping resistor by the fact that this resistor also functions as a DC path to ground for the mode switching diode.

It is the object of the present invention to provide an improved dual mode tuning arrangement with reduced risk of parasitic oscillations and the arrangement according to the invention is therefore characterized by a damping resistor for suppressing parasitic oscillations connected between the second junction of said parallel arrangement and ground.

25

Apart from the reduced risk of parasitic oscillations the arrangement of the present invention has the additional advantage that the desired oscillations are substantially not influenced by the damping resistor and the advantage that the modification can be accomplished without any change of layout of the printed circuit board which usually carries the components of the arrangement.

30

The invention will now be described with reference to the accompanying drawings.

Herein shows:

Fig. 1 a schematic diagram of the prior art dual mode tuning arrangement,

Fig. 2 graphs representing the impedance versus frequency characteristic of the
5 arrangement of figure 1 in both modes,

Fig. 3 a schematic diagram of a dual mode tuning arrangement according to the
invention and.

Fig. 4 graphs representing the impedance versus frequency characteristic of the
10 arrangement of figure 3 in both modes.

10

The tuning arrangement of figure 1 comprises a first series-arrangement of two inductors L_1 and L_2 and a second series-arrangement of a variable capacitance diode C_v and a padding capacitor C_{p1} . The two series arrangements are interconnected at junctions J_1 and J_2 to constitute a parallel arrangement. A small capacitor C_3 is connected in parallel
15 with the variable capacitance diode C_v . The junction J_1 of the two series-arrangements is connected to an amplifier A through a coupling capacitor C_1 and a positive feedback capacitor C_2 . The amplifier A and the two capacitors C_1 and C_2 constitute the active part of the arrangement or current source S that supplies an AC current to the junction J_1 . A tuning voltage V_t is applied through a resistor R_3 to the junction of the variable
20 capacitance diode C_v and the padding capacitor C_{p1} . The tuning voltage may be e.g. be derived from a frequency synthesizer that is located, together with the amplifier A, in a monolithic integrated circuit.

A third series arrangement of a mode switching diode C_{sw} and a second padding
25 capacitor C_{p2} is connected in parallel with the inductor L_2 and a mode-switching voltage V_s is applied to the junction of the mode switching diode and the second padding capacitor through a resistor R_2 . The junction of the inductors L_1 and L_2 is grounded through a relatively small damping resistor R_1 .

30

In operation, during FM reception, no switching voltage is applied through the resistor R_2 and the switching diode C_{sw} behaves like a small capacitor of e.g. 1 pF. In this FM-mode the elements L_1 , L_2 , C_{p1} and $C_v + C_3$ constitute a resonant circuit whose resonant frequency substantially determines the desired oscillator frequency. Varying the tuning
 5 voltage V_t varies this frequency within the range required for tuning within the FM radio band. The values of the padding capacitor C_{p1} and the capacitor C_3 assure that the oscillator frequency substantially tracks with the tuned input circuits (not shown) at a distance of 10,7 MHz.

10 During reception of TV signals a positive voltage V_s is applied through resistor R_2 to the mode switching diode C_{sw} . In this mode the diode C_{sw} behaves like a capacitance of e.g. 1 nF. This capacitance and the padding capacitor C_{p2} bypass the inductor L_2 , so that the resonant circuit is now formed by the elements L_1 , $C_v + C_3$, C_{p1} , C_{p2} and C_{sw} .

15 The resistor R_1 serves to damp any parasitic oscillation of the arrangement. To analyse the parasitic oscillation behaviour of the arrangement it is convenient to consider the active current source S as a negative impedance and to calculate the (positive)
 impedance of the tank circuit (i.e. all elements of the arrangement except the source S) as seen by the current source S . Oscillation will take place at any frequency where the
 20 tank circuit impedance is greater than the negative impedance of the current source. For the determination of the tank-circuit impedance a stray capacitance C_{s1} of the junction $J1$ to ground and a second stray capacitance C_{s2} of the junction of C_{sw} and C_{p2} to ground
 have been taken into account.

25 The impedance of the tank-circuit is shown in figure 2 with the frequency (in MHz) along the horizontal axis and the amplitude of the impedance (in dB) along the vertical axis. For the calculation the following realistic values were chosen:
 $L_1 = 170$ nH, $L_2 = 120$ nH, $R_1 = 5,6$ Ω , $R_2 = 10$ k Ω , $R_3 = 10$ k Ω , $C_3 = 0,5$ pF, $C_{p1} = 120$ nF, $C_{p2} = 220$ nF, $C_{s1} = 0,8$ pF and $C_{s2} = 0,8$ pF.

$C_v = 7,5 \text{ pF}$ which is somewhere in the middle of the tuning range.

$C_{sw} = 1 \text{ pF}$ in FM-mode and 1 nF in TV-mode.

In figure 2 the curve I represents the impedance of the tank-circuit in FM mode and the curve II represents this impedance in TV mode.

5

In TV mode the desired oscillation frequency occurs at the resonance peak R_{II} (approximately 130 MHz). In this mode there is no parasitic resonance within the range of measurement between 0 and 800 MHz. In FM mode the desired oscillation frequency occurs at the resonance peak R_I (approximately 100 MHz). In this mode however, also a
10 parasitic resonance peak P_I exists at approximately 375 MHz. This parasitic resonance is mainly attributed to current travelling in the loop C_{s1}, L_1, R_1 . From the graph of figure 2 it can be seen that the impedance at this parasitic oscillation is only about 10 dB lower than that of the desired oscillation. This is too less to be sure that no parasitic oscillation at this frequency would occur.

15

An improved arrangement is shown in figure 3. The only difference with respect to the arrangement of figure 1 is that the damping resistor R_1 is now replaced by a damping resistor R_{1a} , which is connected between the junction J_2 and ground. Figure 4 shows the impedance-graph of the so modified arrangement with the same values as given above
20 and with the same value for the resistor R_{1a} as for the resistor R_1 of figure 1. The graph shows that the parasitic peak P_I in FM mode is significantly reduced and also shifted away from the desired oscillation frequency (to approximately 500 MHz) so that the risk of parasitic oscillation is substantially minimized. It may also be seen that a parasitic peak P_{II} is now present in the TV mode, however this peak has sufficiently reduced level and a
25 sufficiently low frequency that no risk of parasitic oscillation on this peak exists.


It has to be noted that in the arrangement of figure 3 modifications may be made without departing from the scope of the invention. E.g. the inductor L_1 and the inductor L_2 with parallel connected $C_{sw}-C_{p2}$ combination may be interchanged. Also in the two series
30 arrangements $C_v - C_{p1}$ and $C_{sw} - C_{p2}$ the components may be interchanged with proper choice of the polarity of the respective diode.

IP & S-DE	
zugestellt	
am	23. Juni 2003
Frist	

EPO - Munich
80
01. Aug. 2002

CLAIMS

1. A dual mode tuning arrangement for tuning to VHF television signals and to FM radio signals, said arrangement having a local oscillator circuit comprising a first series arrangement of first and second inductances (L_1 , L_2), a second series arrangement of a variable capacitance diode (C_v) and a first padding capacitor (C_{p1}), said first and second series arrangements being
5 interconnected at first and second junctions (J_1 , J_2) to constitute a parallel arrangement, an active oscillator element (S) being connected between the first junction (J_1) of said parallel arrangement and ground, a third series arrangement of a mode switching diode (C_{sw}) and a second padding capacitor (C_{p2}) connected in parallel with one of said first and second inductances, means (R_3) for supplying a tuning voltage (V_t) to the junction of the variable
10 capacitance diode (C_v) and the first padding capacitor (C_{p1}) and means (R_2) for supplying a mode switching voltage (V_s) to the junction of the mode switching diode (C_{sw}) and the second padding capacitor (C_{p2}), characterized by a damping resistor (R_{1a}) for suppressing parasitic oscillations connected between the second junction (J_2) of said parallel arrangement and ground.



EPO - Munich
80
01. Aug. 2002

ABSTRACT

Dual mode tuning arrangement.

In a local oscillator for a tuning arrangement for both TV and FM signals there is
substantial risk of parasitic oscillation. A special provision is disclosed for effectively
5 reducing this risk.

Fig. 3

01. Aug. 2002




fig. 2




fig. 3




fig. 2




Fig. 2